

TRACK CONNECTORS

120V Track System

WAC LIGHTING

Responsible Lighting®

Fixture Type:

Catalog Number:

Project:

Location:



Track Connectors	Model	Finish	Description
 Live End Connector	HLE H Track	BK Black BN* Brushed Nickel WT White DB** Dark Bronze	Use for direct wiring through ceiling. A canopy plate is required when using with a standard junction box.
	LLE L Track		
	JLE J Track		
	J2-LE J2 Track		
 Live End BX Connector	HBXLE H Track		Use with surface mounted BX or non-metallic sheathed cable. Also provides through the ceiling connection.
	LBXLE L Track		
	JBXLE J Track		
	J2-BXLE J2 Track		
 "I" Power Connector	HI-PWR H Track		Power entry point at the connection of 2 tracks.
	LI-PWR L Track		
	JI-PWR J Track		
	J2-IPWR J2 Track		
 "L" Connector Left	HL-LEFT H Track		Use to join 2 track sections to make power feedable 90° left polarity turns.
	LL-LEFT L Track		
	JL-LEFT J Track		
	J2-LLEFT J2 Track		
 "L" Connector Right	HL-RIGHT H Track		Use to join 2 track sections to make power feedable 90° right polarity turns.
	LL-RIGHT L Track		
	JL-RIGHT J Track		
	J2-LRIGHT J2 Track		
 "T" Connector	HT H Track		Use to join 3 track sections. Power feedable on H and J only. "T" Connector with opposite polarity can be custom ordered.
	LT L Track		
	JT J Track		
	J2-T J2 Track		
 "X" Connector	HX H Track		Use to join 4 track sections. Power feedable on H and J only.
	LX L Track		
	JX J Track		
	J2-X J2 Track		
 "I" Connector	HI H Track		Use to join two sections of track with electrical continuity.
	LI L Track		
	JI J Track		
	J2-I J2 Track		
 "I" Dead End Connector	HI-DEC H Track		Joins two sections of track without electrical continuity.
	LI-DEC L Track		
	JI-DEC J Track		
	J2-IDEC J2 Track		
 Flexible Track Connector	HFLX H Track		Connects two track sections at variable angles. Use as a transition from wall-to-wall, wall-to-ceiling, or ceiling-to-ceiling. Power feedable.
	LFLX L Track		
	JFLX J Track		
	J2-FLX J2 Track		
 Floating Canopy Connector	HFC H Track		Connects to octagon box. Allows track to be powered anywhere along the length of the track.
	LFC L Track		
	JFC J Track		

*BN finish only available for H, L, J Track **DB finish only available for H Track

WAC Lighting

www.waclighting.com

Phone (800) 526.2588 • Fax (800) 526.2585

Headquarters/Eastern Distribution Center

44 Harbor Park Drive • Port Washington, NY 11050

Phone (516) 515.5000 • Fax (516) 515.5050

Western Distribution Center

1750 Archibald Avenue • Ontario, CA 91760

Phone (800) 526.2588 • Fax (800) 526.2585